

# ENERGY STAR<sup>®</sup> Program Requirements for Computers

## APPENDIX A

### ENERGY STAR Test Procedure for Determining the Power Use of Small-Scale Servers and Thin Clients in Off, Sleep, and Idle

The following protocol should be followed when measuring power consumption levels of Small-Scale Servers and Thin Clients for compliance with the Off, Sleep, and Idle levels provided in the ENERGY STAR Version 5.0 Computer Specification. Partners must measure a representative sample of the configuration as shipped to the customer. However, the Partner does not need to consider power consumption changes that may result from component additions, BIOS and/or software settings made by the computer user after sale of product. *This procedure is intended to be followed in order and the mode being tested is labeled where appropriate.*

#### I. Definitions

Unless otherwise specified, all terms used in this document are consistent with the definitions contained in the Version 5.0 ENERGY STAR Eligibility Criteria for Computers.

##### UUT

UUT is an acronym for “unit under test,” which in this case refers to the computer being tested.

##### UPS

UPS is an acronym for “Uninterruptible Power Supply,” which refers to a combination of converters, switches and energy storage means, for example batteries, constituting a power supply for maintaining continuity of load power in case of input power failure.

#### II. Testing Requirements

##### Approved Meter

Approved meters will include the following attributes<sup>1</sup>:

- Power resolution of 1 mW or better;
- An available current crest factor of 3 or more at its rated range value; and
- Lower bound on the current range of 10mA or less.

The following attributes in addition to those above are suggested:

- Frequency response of at least 3 kHz; and
- Calibration with a standard that is traceable to the U.S. National Institute of Standards and Technology (NIST).

It is also desirable for measurement instruments to be able to average power accurately over any user selected time interval (this is usually done with an internal math’s calculation dividing accumulated energy by time within the meter, which is the most accurate approach). As an alternative, the measurement instrument would have to be capable of integrating energy over any user selected time interval with an energy resolution of less than or equal to 0.1 mWh and integrating time displayed with a resolution of 1 second or less.

<sup>1</sup> Characteristics of approved meters taken from IEC 62301 Ed 1.0: Measurement of Standby Power

52 **Accuracy**

53 Measurements of power of 0.5 W or greater shall be made with an uncertainty of less than or equal to  
54 2% at the 95% confidence level. Measurements of power of less than 0.5 W shall be made with an  
55 uncertainty of less than or equal to 0.01 W at the 95% confidence level. The power measurement  
56 instrument shall have a resolution of:  
57

- 58 • 0.01 W or better for power measurements of 10 W or less;
- 59 • 0.1 W or better for power measurements of greater than 10 W up to 100 W; and
- 60 • 1 W or better for power measurements of greater than 100 W.

61  
62 All power figures should be in watts and rounded to the second decimal place. For loads greater than  
63 or equal to 10 W, three significant figures shall be reported.  
64

65 **Test Conditions**

<b>Supply Voltage:</b>	North America/Taiwan:  Europe/Australia/New Zealand:  Japan:	115 (± 1%) Volts AC, 60 Hz (± 1%)  230 (± 1%) Volts AC, 50 Hz (± 1%)  100 (± 1%) Volts AC, 50 Hz (± 1%)/60 Hz (± 1%)  <i>Note: For products rated for &gt; 1.5 kW maximum power, the voltage range is ± 4%</i>
<b>Total Harmonic Distortion (THD) (Voltage):</b>	< 2% THD (< 5% for products which are rated for > 1.5 kW maximum power)	
<b>Ambient Temperature:</b>	23°C ± 5°C	
<b>Relative Humidity:</b>	10 – 80 %	

67 (Reference IEC 62301: Household Electrical Appliances – Measurement of Standby Power, Sections 3.2, 3.3)

68 **Test Configuration**

69 Power consumption of a computer shall be measured and tested from an ac source to the UUT.

70  
71 The UUT must be connected to an Ethernet network switch capable of the UUT's highest and lowest  
72 network speeds. The network connection must be live during all tests.  
73  
74  
75

76 **III. Test Procedure for Off, Sleep and Idle for Small-Scale Servers and Thin Clients**

77 Measurement of ac power consumption of a computer should be conducted as follows:

78 **UUT Preparation**

- 79 1. Record the manufacturer and model name of the UUT.
- 80 2. Ensure that the UUT is connected to network resources as detailed below, and that the UUT  
81 maintains this live connection for the duration of testing, disregarding brief lapses when  
82 transitioning between link speeds.
  - 83 a. Small-Scale Servers shall be connected to a live Ethernet (IEEE 802.3) network switch as  
84 specified in Section II., "Test Configuration," above, and that the connection is live.
  - 85 b. Thin Clients shall be connected to a live server via a live Ethernet (IEEE 802.3) network  
86 switch and shall run intended terminal/remote connection software.
- 87 3. Connect an approved meter capable of measuring true power to an ac line voltage source set to  
88 the appropriate voltage/frequency combination for the test.  
89

- 90 4. Plug the UUT into the measurement power outlet on the meter. No power strips or UPS units  
91 should be connected between the meter and the UUT. For a valid test to take place the meter  
92 should remain in place until all Off, Sleep, and Idle power data is recorded.
- 93 5. Record the ac voltage.
- 94 6. Boot UUT and wait until the operating system has fully loaded.
- 95 7. If necessary, run the initial operating system setup and allow all preliminary file indexing and other  
96 one-time/periodic processes to complete.
- 97 8. Record basic information about the computer's configuration – computer type, operating system  
98 name and version, processor type and speed, and total and available physical memory, etc.<sup>2</sup>
- 99 9. Record basic information about the video card or graphics chipset (if applicable) - video  
100 card/chipset name, resolution, amount of onboard memory, and bits per pixel.<sup>3</sup>
- 101 10. Ensure that the UUT is configured as shipped including all accessories, power management  
102 settings, WOL enabling and software shipped by default. UUT should also be configured using  
103 the following requirements for all tests:
- 104 a. Small-Scale Servers and thin clients shipped without accessories should be configured  
105 with a standard mouse, keyboard and external monitor (if server has display output  
106 functionality).
- 107 b. Power to wireless radios should be turned off for all tests. This applies to wireless  
108 network adapters (e.g., 802.11) or device-to-device wireless protocols.
- 109 11. The following guidelines should be followed to configure power settings for displays (adjusting no  
110 other power management settings):
- 111 a. For computers with external displays: use monitor power management settings to prevent  
112 the monitor from powering down to ensure it stays on for the full length of the Idle test as  
113 described below.
- 114 b. For computers with integrated displays: if power management settings are available, use  
115 power management settings available to users of the UUT to set the monitor to power  
116 down after 1 minute.
- 117 12. Shut down the UUT.

#### 118 **Off Mode Testing**

- 119 13. With the UUT shut down and in Off, set the meter to begin accumulating true power values at an  
120 interval of 1 reading per second. Accumulate power values for 5 additional minutes and record  
121 the average (arithmetic mean) value observed during that 5 minute period.<sup>4</sup>

#### 122 **Idle Mode Testing**

- 123 14. Switch on the computer and begin recording elapsed time, starting either when the computer is  
124 initially switched on, or immediately after completing any log in activity necessary to fully boot the  
125 system. Once logged in with the operating system fully loaded and ready, close any open  
126 windows so that the standard operational desktop screen or equivalent ready screen is displayed.  
127 Between 5 and 15 minutes after the initial boot or log in, set the meter to begin accumulating true  
128 power values at an interval of 1 reading per second. Accumulate power values for 5 additional  
129 minutes and record the average (arithmetic mean) value observed during that 5 minute period.

#### 130 **Sleep Mode Testing (*Thin Clients, only*)**

- 131 15. After completing the Idle measurements, place the computer in Sleep mode. Reset the meter (if  
132 necessary) and begin accumulating true power values at an interval of 1 reading per second.

133 <sup>2</sup> On Windows-based machines, much of this information can be found by selecting the following window: Start /  
134 Programs / Accessories / System Tools / System Information.

135 <sup>3</sup> On Windows-based machines, this can be found by selecting the following window: Start / Programs / Accessories /  
System Tools / Components / Display.

<sup>4</sup> Laboratory-grade, full-function meters can integrate values over time and report the average value automatically.  
Other meters would require the user to capture a series of changing values every 5 seconds for a five minute period  
and then compute the average manually.

136 Accumulate power values for 5 additional minutes and record the average (arithmetic mean) value  
137 observed during that 5 minute period.  
138 16. If testing both WOL enabled and WOL disabled for Sleep, wake the computer and change the  
139 WOL from Sleep setting through the operating system settings or by other means. Place the  
140 computer back in Sleep mode and repeat step 14, recording Sleep power necessary for this  
141 alternate configuration.  
142

143 **Reporting Test Results**

144 17. The test results must be reported to EPA or the European Commission, as appropriate, taking  
145 care to ensure that all required information has been included.  
146

147 **IV. Continuing Verification**

148 This testing procedure describes the method by which a single unit may be tested for compliance. An  
149 ongoing testing process is highly recommended to ensure that products from different production runs  
150 are in compliance with ENERGY STAR.  
151  
152