

ENERGY STAR® Program Requirements Product Specification for Data Center Storage

Draft Test Method Rev. April 2020

Note: EPA has been coordinating with the Storage Networking Industry Association (SNIA) as it develops
the Emerald Version 4.0.0 test method in an effort to utilize the latest test method as part of the ENERGY
STAR Version 2.0 Data Center Storage specification testing protocol. EPA is pleased to update the
ENERGY STAR test method to incorporate the new Emerald Version 4.0.0 test method and associated
updates. EPA has not amended any other elements of the test method at this time. It is the Agency's
understanding that results from the previous Emerald test method may be used to certify products to the
Version 2.0 specification.

8 1 OVERVIEW

9 The following test method shall be used for determining compliance with requirements in the ENERGY
 10 STAR Product Specification for Data Center Storage.

11 2 APPLICABILITY

The following test method is applicable to all products eligible for certification under the ENERGY
 STAR Product Specification for Data Center Storage.

14 3 DEFINITIONS

Unless otherwise specified, all terms used in this document are consistent with the definitions in the
 ENERGY STAR Eligibility Criteria for Data Center Storage.

17 4 TEST SETUP

18

19

- A) <u>Input Power</u>: Input power shall be as specified in Table 1 and Table 2. The frequency for input power shall be as specified in Table 3.
- B) <u>Ambient Temperature</u>: Ambient temperature shall be no less than 18 °C and no greater than 28 °C over the duration of the test.
- 22 C) <u>Relative Humidity</u>: Relative humidity shall be within 15% and 80%.

23 24

Table 1: Input Power Requirements for Products with Nameplate Rated Power Less Than or Equalto 1500 W

Product Type	Supply Voltage	Voltage Tolerance	Maximum Total Harmonic Distortion
Storage Products with Ac- Dc Single-Output PSUs	230 volts (V) ac or 115 V ac		
Storage Products with Ac- Dc Multi-Output PSUs	230V ac or 115V ac		
Optional Testing Conditions For Ac-Dc Japanese Market	100V ac	+/- 1.0 %	2.0 %
Three-phase Storage Products (North American Market)	208V ac		
Three-phase Storage Products (European Market)	400V ac		

25 26

Table 2: Input Power Requirements for Products with Nameplate Rated Power Greater Than1500 W

Product Type	Supply Voltage	Voltage Tolerance	Maximum Total Harmonic Distortion
Storage Products with Ac-Dc Single-Output PSUs	230 volts (V) ac or 115 V ac		
Storage Products with Ac-Dc Multi-Output PSUs	230V ac or 115V ac		5.0 %
Optional Testing Conditions For Ac-Dc Japanese Market	100V ac	+/- 5.0 %	
Three-phase Storage Products (North American Market)	208V ac		
Three-phase Storage Products (European Market)	400V ac		

Table 3: Input Frequency Requirements for All Products

Supply Voltage	Frequency	Frequency Tolerance	
100 V ac	50 or 60 Hz		
115 V ac	60 Hz	±1.0%	
230 V ac	50 Hz or 60 Hz		
Three-phase	50 Hz or 60 Hz		

D) <u>Power Meter</u>: Power Meter(s) shall report true Root Mean Square (RMS) power and at least two of the following measurement units: voltage, current and power factor. Power Meter(s) shall possess the following attributes:

- 1) <u>Calibration</u>: The meter shall be calibrated within the past one year of the test date, by a standard traceable to National Institute of Science and Technology (USA) or a counterpart national metrology institute in other countries.
- <u>Crest Factor</u>: An available current crest factor of 3 or more at its rated range value. For analyzers that do not specify the current crest factor, the analyzer must be capable of measuring an amperage spike of at least 3 times the maximum amperage measured during any 1 second sample.
- 3) Minimum Frequency Response: 3.0 kHz
- Minimum Resolution:
 - i. 0.01 W for measurement values less than 10 W;
 - ii. 0.1 W for measurement values from 10 W to 100 W; and
 - iii. 1.0 W for measurement values greater than 100 W.
 - 5) Logging: The reading rate supported by the meter shall be at least 1 set of measurements per second, where set is defined as watts. The data averaging interval of the analyzer shall equal the reading interval. Data averaging interval is defined as the time period over which all samples captured by the high-speed sampling electronics of the analyzer are averaged to provide the measurement set.
 - 6) <u>Measurement Accuracy</u>: Measurement uncertainty as introduced by the instrument that measures the input power to the product under test, including any external shunts.
 - i. Power measurements with a value greater than or equal to 0.5 W shall be made with an uncertainty of less than or equal to 2% at the 95% confidence level.
 - ii. Power measurements with a value less than 0.5 W shall be made with an uncertainty of less than or equal to 0.01 W at the 95% confidence level.
- 55 E) Temperature Sensor: The temperature sensor shall possess the following attributes:
 - 1) Logging: The sensor shall have a minimum reading rate of 4 samples per minute.

27

28 29

30

31 32

33

34

35

36

37

38

39 40

41

42

43

44

45

46 47

48 49

50

51

52

53

54

56

59 accuracy of ± 0.5 °C or better. 5 TEST CONDUCT 60 Guidance for Implementation of SNIA Emerald[™] Power Efficiency Measurement 5.1 61 Specification Version 4.0.0 62 63 64 A) Storage products shipped with COMs must disable all COMs that are capable of being disabled 65 during the following tests: 1) SUT Pre-fill Test (7.3.3) 66 67 2) SUT Conditioning Test (7.3.4) 3) Block Access Active State Test (7.3.5, if applicable) 68 69 4) File Access Active Test (7.4, if applicable) 70 5) Ready State Idle Test (7.5) 71 Following the completion of the Ready Idle State Test, COMs shipped with the storage product shall be enabled and COM Validation Testing (7.6) shall be performed for all COMs 72

B) Products that are to be certified using Block I/O capability shall be tested using the Block I/O Active State Test. Block I/O products with File I/O capability shall be tested under the following additional requirements:

2) Measurement Accuracy: Temperature must be measured no more than 50 mm in front of

(upwind of) the main airflow inlet of the UUT and reported by the sensor with an overall

1) All usable Storage Devices shall be allocated to Block I/O for all testing with the exception of:

- i. Storage Devices needed to enable a minimal File I/O capability in the system;
- ii. Limitations imposed by the system for maximum allowable Block I/O capacity.
- 2) File I/O functionality shall be enabled during all testing.

present in the product.

- No external File I/O storage requests shall be presented to a system during testing. (File I/O functionality shall be in a Ready-Idle state).
- 84 C) Products that are to be certified using File I/O capability shall be tested using the File I/O Active
 85 State Test.

6 TEST PROCEDURES FOR ALL PRODUCTS

87 6.1 SUT Pre-fill Test

57

58

73 74 75

76

77

79

80

81 82

83

The SUT pre-fill test shall be performed according to the SNIA Emerald[™] Power Efficiency Measurement
 Specification Version 4.0.0: Section 7.3.3: *Pre-fill Test*.

90 6.2 SUT Conditioning Test

- 91 The SUT conditioning shall be performed according to the SNIA Emerald[™] Power Efficiency
- 92 Measurement Specification Version 4.0.0: Section 7.3.4: Conditioning Test.

93 6.3 Block I/O Active State Test

ENERGY STAR Program Requirements for Data Center Storage - Final Test Method (Rev. April 2020)

- 94 The Block I/O active state performance shall be measured according to the SNIA Emerald[™] Power
- 95 Efficiency Measurement Specification Version 4.0.0: Section 7.3.5: Block Access Active Test; with the 96 additional guidance in Section 5 of this document.

97 6.4 File I/O Active State Test

98 The File I/O active state performance shall be measured according to the SNIA Emerald[™] Power
 99 Efficiency Measurement Specification Version 4.0.0: Section 7.4: File Access Active Test; with the
 100 additional guidance in Section 5 of this document.

101 6.5 Ready Idle State Test

The Ready Idle state performance shall be measured according to the SNIA Emerald[™] Power Efficiency
 Measurement Specification Version 4.0.0: Section 7.5: Random Block and File Access Ready Idle Test;
 with the additional guidance in Section 5 of this document.

105 6.6 COM Validation Test

The validation of COM functionality shall be recorded according to the SNIA Emerald[™] Power Efficiency
 Measurement Specification Version 4.0.0: Section 7.6: Random Block and File Access Capacity
 Optimization Test, with the additional guidance in Section 5 of this document.

A) Verification testing of COM features specified by the storage product shall be executed at least once using storage devices of the vender's choice. Once verified there is no requirement to reexecute the verification testing procedure with different storage devices.

112 113

110

111